





# Downlighter Corridor





The Alba Downlighter products are intelligent high specification emergency LED luminaires. Alba utilizes the latest LED and optic technology to provide a high quality and high performance luminaire for indoor use where aesthetics are of prime importance.

The Alba Downlighter Corridor has been designed for ease of installation with minimal maintenance without compromising on aesthetics. The device is particularly suited for extra low voltage control panel based emergency lighting and evacuation lighting applications. The innovative optic design utilizes light efficiently from the LED to provide a uniform distribution in escape route corridor spaces.

Housing Colour	White (RAL 9003) & Gray (Pantone 429)
Housing Material	PC/ABS 2950
Battery Pack	4xNiMh AAA 600mA
Weight inc. batteries	229 grams
Dimensions	120 mm x 43 mm
Operation Time	3 Hours



 4.8v.0.6Ah Ni-Mh  180 min



Mounting Height	Spacing to wall	Spacing between Downlighters
2.0 m	4.5 m	13.0 m
2.5 m	2.4 m	12.7 m




# Downlighter Open Area





The Alba Downlighter products are intelligent high specification emergency LED luminaires. Alba utilizes the latest LED and optic technology to provide a high quality and high performance luminaire for indoor use where aesthetics are of prime importance.

The Alba Downlighter Open Area has been designed for ease of installation with minimal maintenance without compromising on aesthetics. The device is particularly suited for extra low voltage control panel based emergency lighting and evacuation lighting applications. The innovative optic design utilizes light efficiently from the LED to provide a uniform distribution in open area anti-panic spaces.

Housing Colour	White (RAL 9003) & Gray (Pantone 429)
Housing Material	PC/ABS 2950
Battery Pack	4xNiMh AAA 600mA
Weight inc. batteries	229 grams
Dimensions	120 mm x 43 mm
Operation Time	3 Hours



 4.8v.0.6Ah Ni-Mh  180 min



Mounting Height	Spacing to wall	Spacing between Downlighters
2.0 m	2.3 m	7.4 m
2.5 m	2.4 m	8.1 m